POWER SFLEET

Script.Serial.KN02_V5_FORKLIFT_GKN_130000_236_DC_RF_V1.0.0.0

FORKLIFT KNOV KN02 GKN 130000 236 DC RF Serial Script



Overview

POWER©FLEET°

This script has been developed to support a maintenance checklist for Forklifts at customer GKN (Brazil). The forklift operator shall answer several questions about the vehicle status. Depending on the answers, the vehicle should be released for operation or blocked.

The script is not aimed at a particular forklift type or brand. It implements a process, controlling a low-cost keyboard, the KN02-Max. The KN02-Max has been fitted with a custom skin for MiX Telematics (shown above).

This script is a customized version of the template "Maintenance Checklist for Forklifts – V5".

People Powered AloT

POWERSFLEET

The template has been modified to support:

- 13 questions (all with engine ON)
- Critical questions: (2, 3, 5, 6, 10) => Mask 236h
- Mode of Operation: Change of driver
- Identification Mode: RFID Card (using keyboard's embedded RFID reader)
- Master Card ID- range: 0x04D5B7BD to 0x04D5B821
- Maintenance Card ID range 0x109647A4 to 0x10964808

See template documentation for details about the operation of the script.

This script can be used with the following devices:

- 1. MiX 4000
- 2. MiX 6000
- 3. FM3316 and FM3306 Communicators
- 4. FM3517i and FM3507i Communicators
- 5. FM3617i and FM3607i Communicators
- 6. FM3717i and FM3707i Communicators
- 7. FM3817i and FM3807i Communicators

Version History

Reference	Version	Changes	
<u>ESCR-125</u>	V1.0.0.0	 First version for customer GKN. Based on Maintenance Checklist for Forklifts V5. 13 questions (all with engine ON) Critical questions: (2, 3, 5, 6, 10) => Mask 236h Mode of Operation: Change of driver Identification Mode: RFID Card (using keyboard's embedded RFID reader) Master Card ID- range: 0x04D5B7BD to 0x04D5B821 Maintenance Card ID range 0x109647A4 to 0x10964808 	
ESCR-125	V1.0.0.0	Converted script to Production.	

POWER SFLEET

Supported Parameters

ACRONYM	PARAMETER NAME	PARAMETER DESCRIPTION	Return values/states (if applicable)
FKQID	FORK.Question_ID	Indicates the Question ID processed	Range 1 and 32
FKQTP	FORK.Question_Type	Indicates if a Question is critical or not*	0 = noncritical 1 = critical
FKQAW	FORK.Question_Answer	Indicates the Answer (YES/NO) received	0 = No 1 = Yes
FKDID	FORK.Driver_ID	Current Driver ID	
FKCHS	FORK.Checklist_Status	Indicates the current Checklist status	See table below
FKERR	FORK.Error_Msg	Reserved	Not used

POWER SFLEET

FORK.Checklist_Status

STATUS	MEANING		
0	Ignition is OFF (Vehicle not being used).		
1	Vehicle has been released for use => checklist has been performed, and no critical issues have been reported		
2	Vehicle has been blocked => checklist has been performed and at least one critical issue was reported		
3	Vehicle has been released => checklist not performed because it has been previously successfully performed in the same work shift or due to change of driver).		
4	Vehicle has been released due to special authorization => Driver uses a forklift in special authorization mode		
5	Vehicle in Maintenance Mode => attempt to use a vehicle in maintenance mode		
6	First part of the Checklist has been finished, and driver informs that engine was successfully turned ON		
7	Vehicle has been released due to relocation - Driver uses a forklift in relocation mode		
8	Attempt to use a forklift which has been blocked in the previous operation. A message has been displayed informing that the forklift has been previously blocked.		
9	The checklist has been cancelled but vehicle is blocked=> ignition was turned off during checklist operation, but vehicle is blocked as a critical question got a negative answer		
10	Checklist Part 1 has been started		
11	Configuration has been aborted (maintenance or Admin menus) and Vehicle is blocked => ignition was turned off during checklist operation, but vehicle is blocked.		
12	Checklist Part 3 has been started		
13	Checklist cancelled (ignition was turned Off)		
14	The vehicle has been enabled by Supervisor (using Admin Card)		
15	Vehicle has been disabled by Supervisor (using Admin Card)		
16	The vehicle remains enabled and unblocked		
17	Admin Menu has been started		
18	Vehicle remains disabled		
19	The vehicle remains blocked		

POWERSFLEET

People Powered AloT

20	Unblock vehicle (using Amin Card) due to error in answering the checklist		
21	Released vehicle due to special authorization by Admin=> (vehicle released for use during current work shift or till next change of driver		
22	Released vehicle for relocation performed by Admin=> vehicle released for use during one trip, afterwards it is blocked again		
23	Maintenance Menus has been started		
24	The vehicle has been enabled by Maintenance		
25	Vehicle remains enabled		
26	Vehicle disabled by maintenance and out of maintenance		
27	Vehicle disabled by maintenance and Into Maintenance		
28	Vehicle is out of Maintenance		
29	Vehicle remains in Maintenance		
30	Configuration has been aborted (maintenance or Admin menus) => ignition was turned off during checklist operation. The vehicle is not blocked.		
31	Attempt to use a disabled vehicle		
32	Engine has been unblocked		
33	Checklist Part 2 has been started		

Installation Notes

- 1. Direct connection between KNOV KN02 keyboard and OBC using the serial interface (DB9)
- 2. Communication Settings:
 - Baud Rate = 19200
 - Data Bits = 8
 - Parity = None
 - Stop Bits = 1